


# Coaxlink Duo

Two-connection CoaXPress frame grabber



## At a Glance

- Two CoaXPress CXP-6 connections: 1,250 MB/s camera bandwidth
- PCIe 2.0 (Gen 2) x4 bus: 1,700 MB/s delivery bandwidth
- Feature-rich set of 20 digital I/O lines
- Extensive camera control functions
- Memento Event Logging Tool

## Benefits

### Acquire images from the fastest and highest resolution cameras

- Highest data acquisition rate in the industry
- 12.5 Gbit/s (1,250 MB/s) bandwidth from camera to host PC memory

### Use standard coaxial cables

- A single inexpensive cable for data transfer, camera control, trigger and power supply
- Top reliability and flexibility, performs in the harshest environments

### Long cable support

- 40 meters at CXP-6 speed (6.25 Gbps)
- 100 meters at CXP-3 speed (3 Gbps)

### Robust connectors

Coaxlink uses DIN 1.0/2.3 connectors with push/pull latching system for reliable connections

### Memento Event Logging Tool

- Memento is an advanced development and debugging tool available for Coaxlink cards.
- Memento records an accurate log of all the events related to the camera, the frame grabber and its driver as well as the application.
- It provides the developer with a precise timeline of time-stamped events, along with context information.
- It provides valuable assistance during application development and debugging, as well as during machine operation.

## **Direct GPU transfer**

- Sample programs for AMD DirectGMA and NVIDIA (CUDA) available.
- Direct GPU transfer eliminates unnecessary system memory copies, dramatically lowers CPU overhead, and reduces latency, resulting in significant performance improvements in data transfer times for applications.
- Direct capture of image data to GPU memory is available using AMD's DirectGMA. Compatible with AMD FirePro W5x00 and above and all AMD FirePro S series products.

## **PCIe 2.0 (Gen 2) x4 bus**

- 1,700 MB/s sustained bus bandwidth

## **General purpose I/O lines**

- Compatible with a wide range of sensors and motion encoders.
- High-speed differential inputs: Quadrature motion encoder support up to 5 MHz.
- Isolated current-sense inputs: 5V, 12V, 24V signaling voltages accepted, up to 50 kHz, individual galvanic isolation up to 500VAC RMS.
- Isolated contact outputs.
- High-speed 5V-compliant TTL inputs/ LVTTTL outputs.

## **High-performance DMA (Direct Memory Access)**

- Direct transfer into user-allocated memory
- Hardware scatter-gather support
- 64-bit addressing capability

## **Area-scan triggering capabilities**

- A trigger is used to start the acquisition when the part is in position. Hardware triggers come from the Coaxlink's I/O lines. Software triggers come from the application.
- An optional trigger delay is available to postpone the acquisition for a programmable time.
- A trigger decimation function allows to skip some of the triggers.
- Camera exposure control allows the application to control the exposure time of the camera.
- When the acquisition starts, at the appropriate timing, the Coaxlink board generates a signal to control an illumination device connected to one of its output lines.

## **The Coaxlink driver includes the following tools:**

- Genicam Browser: An application giving access to the GenICam features exposed by the GenTL Producer(s) in the system.
- GenTL Console: A command-line tool giving access to the functions and commands exposed by the Euresys GenTL Producer.

## **Compliant with Genicam**

Including support for

- GenApi
- The Standard Feature Naming Convention (SFNC)
- GenTL

## **Windows and Linux drivers available**

- Including support for the AArch64 64-bit ARM architecture for Linux

## Applications

### **MACHINE VISION FOR THE ELECTRONIC MANUFACTURING INDUSTRY**

#### **High speed image acquisition for inspection machines.**

The Coaxlink and Grablink cards are dependable industrial frame grabbers that provide robust and stable image acquisition from the fastest digital cameras available. They feature precise camera control and synchronization functions.

- AOI (Automated Optical Inspection) machines
- 3D SPI (Solder Paste Inspection) machines
- 3D lead/ball inspection machines

### **MACHINE VISION FOR THE GENERAL MANUFACTURING INDUSTRIES**

#### **High frame rate image acquisition for inspection machines**

Glass inspection: bottles, vials

#### **Image acquisition for robots**

### **VIDEO ACQUISITION AND RECORDING**

#### **High-frame-rate video acquisition for motion analysis and recording**

### **VIDEO MONITORING, SURVEILLANCE & SECURITY**

#### **Transmission and acquisition of high-definition video over long coaxial cables for traffic surveillance, monitoring and control**

CoaXPress is a recent powerful standard providing a high speed interface between the camera and the PC frame grabber. On a highway, high speed cameras can take images in a burst. The sharper images will enhance license plate recognition accuracy.

High frequency real time triggering and exposure time adjustment to the low light situations can be accommodated.

## Specifications

### Mechanical

Form Factor	PCI Express card
Format	Standard profile, half length, 4-lane PCI Express card
Cooling method	Air cooling, fan-cooled heatsink
Mounting	For insertion in a standard height, 4-lane or higher, PCI Express card slot
Connectors	<ul style="list-style-type: none"><li>• 'A', 'B' on bracket:<ul style="list-style-type: none"><li>– 2x DIN 1.0/2.3 female connectors</li><li>– CoaXpress host interface</li></ul></li><li>• EXTERNAL I/O' on bracket:<ul style="list-style-type: none"><li>– 26-pin 3-row high-density female sub-D connector</li><li>– I/O lines and power output</li></ul></li><li>• INTERNAL I/O 1' and 'INTERNAL I/O 2' on PCB:<ul style="list-style-type: none"><li>– 2x 26-pin 2-row 0.1" pitch pin header with shrouding</li><li>– I/O lines and power output</li></ul></li><li>• 'AUXILIARY POWER INPUT' on module:<ul style="list-style-type: none"><li>– 6-pin PEG power socket</li><li>– 12 VDC power input for PoCXP camera(s) and I/O power</li></ul></li><li>• 'C2C-LINK' on module:<ul style="list-style-type: none"><li>– 6-pin 2-row 0.1-in header</li><li>– Card to card link</li></ul></li></ul>
Lamp indicators	<ul style="list-style-type: none"><li>• 'A', 'B' on bracket:<ul style="list-style-type: none"><li>– 2x Bi-color red/green LEDs</li><li>– CoaXPress Host connector indicator lamps</li></ul></li><li>• 'FPGA STATUS LAMP' on PCB:<ul style="list-style-type: none"><li>– Bi-color red/green LED</li><li>– FPGA status lamp</li></ul></li><li>• 'BOARD STATUS LAMP' on PCB:<ul style="list-style-type: none"><li>– Bi-color red/green LED</li></ul></li></ul>
Switches	<p>'RECOVERY' on card PCB:</p> <ul style="list-style-type: none"><li>• 3-pin 1-row 0.1" header</li><li>• Firmware emergency recovery</li></ul>
Dimensions	L 167.65 mm x H 111.15 mm L 6.6 in x H 4.38 in
Weight	160 g, 5.64 oz

## Host bus

Standard	PCI Express 2.0
Link width	<ul style="list-style-type: none"> <li>• 4 lanes</li> <li>• 1 lane or 2 lanes with reduced performance</li> </ul>
Link speed	<ul style="list-style-type: none"> <li>• 5.0 GT/s (PCIe 2.0)</li> <li>• 2.5 GT/s (PCIe 1.0) with reduced performance</li> </ul>
Maximum payload size	512 bytes
DMA	32- and 64-bit
Peak delivery bandwidth	2,000 MB/s
Effective (sustained) delivery bandwidth	1,700 MB/s (Host PC motherboard dependent)
Power consumption	Typ. 11.4 W ( 2.7 W @ +3.3V, 8.7 W @ +12V), excluding camera and I/O power output

## Camera / video inputs

Interface standard(s)	CoaXPress 1.0 and 1.1
Connectors	2x DIN1.0/2.3 CXP-6
Status LEDs	1 CoaXPress Host connection status per connector
Number of cameras	<ul style="list-style-type: none"> <li>• One 1- or 2-connection area-scan camera</li> <li>• Two 1-connection area-scan cameras</li> </ul>
Line-scan cameras supported	No
Maximum aggregated camera data transfer rate	12.5 Gbit/s (1,250 MB/s)
Supported CXP down-connection speeds	1.25 GT/s (CXP-1), 2.5 GT/s (CXP-2), 3.125 GT/s (CXP-3), 5 GT/s (CXP-5), and 6.25 GT/s (CXP-6)
Number of CXP data streams (per camera)	1 data stream per camera
Maximum CXP stream packet size	16,384 bytes
PoCXP (Power over CoaXPress)	<ul style="list-style-type: none"> <li>• PoCXP Safe Power: <ul style="list-style-type: none"> <li>– 17 W of 24V DC regulated power per CoaXPress connector</li> <li>– PoCXP Device detection and automatic power-on</li> <li>– Overload and short-circuit protections</li> </ul> </li> <li>• On-board 12V to 24V DC/DC converter</li> <li>• A +12V power source must be connected to the AUXILIARY POWER INPUT connector using a 6-pin PEG cable</li> </ul>
Camera types	<ul style="list-style-type: none"> <li>• Area-scan cameras: <ul style="list-style-type: none"> <li>– Gray-scale and color (RGB and Bayer CFA)</li> <li>– Single-tap (1X-1Y) progressive-scan</li> </ul> </li> </ul>
Camera pixel formats supported	Raw, Monochrome, Bayer, RGB, and RGBA (PFNC names): <ul style="list-style-type: none"> <li>• Raw</li> <li>• Mono8, Mono10, Mono12, Mono14, Mono16</li> <li>• BayerXX8, BayerXX10, BayerXX12, BayerXX14, BayerXX16 where XX = GR, RG, GB, or BG</li> <li>• RGB8, RGB10, RGB12, RGB14, RGB16</li> <li>• RGBA8, RGBA10, RGBA12, RGBA14, RGBA16</li> </ul>

## Area-scan camera control

Trigger	<ul style="list-style-type: none"><li>• Precise control of asynchronous reset cameras, with exposure control.</li><li>• Support of camera exposure/readout overlap.</li><li>• Support of external hardware trigger, with optional delay and trigger decimation.</li></ul>
Strobe	<ul style="list-style-type: none"><li>• Accurate control of the strobe position for strobed light sources.</li><li>• Support of early and late strobe pulses.</li></ul>

## On-board processing

On-board memory	1 GB
Image data stream processing	<ul style="list-style-type: none"><li>• Unpacking of 10-/12-/14-bit to 16-bit with selectable justification to LSb or MSb</li><li>• Optional swap of R and B components</li><li>• Little endian conversion</li></ul>
Data stream statistics	<ul style="list-style-type: none"><li>• Measurement of:<ul style="list-style-type: none"><li>– Frame rate (Area-scan only)</li><li>– Line rate</li><li>– Data rate</li></ul></li><li>• Configurable averaging interval</li></ul>
Event signaling and counting	<ul style="list-style-type: none"><li>• The application software can be notified of the occurrence of various events:<ul style="list-style-type: none"><li>– Standard event: the EVENT_NEW_BUFFER event notifies the application of newly filled buffers</li><li>– A large set of custom events</li></ul></li><li>• Custom events sources:<ul style="list-style-type: none"><li>– I/O Toolbox events</li><li>– Camera and Illumination control events</li><li>– CoaXPress data stream events</li><li>– CoaXPress host interface events</li></ul></li><li>• Each custom event is associated with a 32-bit counter that counts the number of occurrences</li><li>• The last three 32-bit context data words of the event context data can be configured with event-specific context data:<ul style="list-style-type: none"><li>– Event-specific data</li><li>– State of all System I/O lines sampled at the event occurrence time</li><li>– Value of any event counter</li></ul></li></ul>
Input LUT (Lookup Table)	<ul style="list-style-type: none"><li>• Available for monochrome cameras<ul style="list-style-type: none"><li>– 8 to 8 bits</li><li>– 10 to 8, 10 or 16 bits</li><li>– 12 to 8, 12 or 16 bits</li></ul></li></ul>

## General Purpose Inputs and Outputs

Number of lines	20 I/O lines: <ul style="list-style-type: none"><li>• 4 differential inputs (DIN)</li><li>• 4 singled-ended TTL inputs/outputs (TTLIO)</li><li>• 8 isolated inputs (IIN)</li><li>• 4 isolated outputs (IOUT)</li></ul>
-----------------	--

Usage	<ul style="list-style-type: none"> <li>Any System I/O input lines can be used by any LIN tool of the I/O Toolbox</li> <li>Selected pairs of System I/O input lines can be used by any QDC tool of the I/O toolbox to decode A/B signals of a motion encoder</li> <li>The LIN and QDC tools outputs can be further processed by the other tools (DIV, MDV, DEL) of the I/O toolbox to generate any of the following "trigger" events: <ul style="list-style-type: none"> <li>The "cycle trigger" of the Camera and Illumination controller</li> <li>The "cycle sequence trigger" of the Camera and Illumination controller</li> <li>The "start-of-scan trigger" of the Acquisition Controller (line-scan only)</li> <li>The "end-of-scan trigger" of the Acquisition Controller (line-scan only)</li> </ul> </li> </ul>
Electrical specifications	<ul style="list-style-type: none"> <li>DIN: High-speed differential inputs compatible with ANSI/EIA/TIA-422/485 differential line drivers and complementary TTL drivers</li> <li>TTLIO: High-speed 5V-compliant TTL inputs or LVTTL outputs, compatible with totem-pole LVTTL, TTL, 5V CMOS drivers or LVTTL, TTL, 3V CMOS receivers</li> <li>IIN: Isolated current-sense inputs with wide voltage input range up to 30V, compatible with totem-pole LVTTL, TTL, 5V CMOS drivers, RS-422 differential line drivers, potential free contacts, solid-state relays and opto-couplers</li> <li>IOUT: Isolated contact outputs compatible with 30V / 100mA loads</li> </ul>
Filter control	<ul style="list-style-type: none"> <li>Glitch removal filter available on all System I/O input lines</li> <li>Configurable filter time constants: <ul style="list-style-type: none"> <li>for DIN and TTLIO lines: 50 ns, 100 ns, 200 ns, 500 ns, 1 <math>\mu</math>s</li> <li>for IIN lines: 500 ns, 1 <math>\mu</math>s, 2 <math>\mu</math>s, 5 <math>\mu</math>s, 10 <math>\mu</math>s</li> </ul> </li> </ul>
Polarity control	Yes
Power output	Non-isolated, +12V, 1A, with electronic fuse protection
I/O Toolbox tools	<p>The I/O Toolbox is a configurable interconnection of tools that generates events (usually triggers) from input lines. The composition of the toolset is product- and firmware-dependent.</p> <ul style="list-style-type: none"> <li>Line Input tool (LIN): Edge detector delivering events on rising or falling edges of any selected input line.</li> <li>Quadrature Decoder tool (QDC): A composite tool including: <ul style="list-style-type: none"> <li>A quadrature edge detector delivering events on selected transitions of selected pairs of input lines.</li> <li>An optional backward motion compensator for clean line-scan image acquisition when the motion is unstable.</li> <li>A 32-bit up/down counter for delivering a position value.</li> </ul> </li> <li>Divider tool (DIV): to generate an event every nth input events from any I/O toolbox event source.</li> <li>Multiplier/divider tool (MDV): to generate m events every d input events from any I/O toolbox event source.</li> <li>Delay tool (DEL): to delay up to 16 events from one or two I/O toolbox event sources, by a programmable time or number of motion encoder ticks (any QDC events).</li> <li>User Actions Scheduler tool (UAS): to delegate the execution of User Actions at a scheduled time or encoder position. Possible user actions include setting low/high/toggle any bit of the User Output Register or generation of any User Events.</li> </ul>
I/O Toolbox composition	<p>Firmware-dependent I/O toolbox composition:</p> <ul style="list-style-type: none"> <li>1-camera: 8 LIN, 1 QDC, 1 DIV, 1 MDV, 2 DEL, 1 UAS</li> <li>2-camera: 8 LIN, 1 QDC, 1 DIV, 1 UAS</li> </ul>

## C2C-Link

Description	<ul style="list-style-type: none"><li>• Allows to accurately synchronize the trigger and start-of-exposure of multiple grabber-controlled area-scan and line-scan cameras.</li><li>• C2C-Link is able to synchronize cameras connected<ul style="list-style-type: none"><li>– to the same Coaxlink card</li><li>– to different cards in the same PC (requires an accessory cable such as the "3303 C2C-Link Ribbon Cable" or a custom-made C2C-Link cable)</li><li>– to different cards in different PCs (requires one "1636 InterPC C2C-Link Adapter" for each PC and one RJ 45 CAT 5 STP straight LAN cable for each adapter but the last one)</li></ul></li></ul>
Specification	<ul style="list-style-type: none"><li>• Maximum distance<ul style="list-style-type: none"><li>– 60 cm inside a PC</li><li>– 1200 m cumulated adapter to adapter cable length</li></ul></li><li>• Maximum trigger rate<ul style="list-style-type: none"><li>– 2.5 MHz for configurations using a single PC, or up to 10 PCs and 100 m total C2C-Link cable length</li><li>– 200 kHz for configurations up to 32 PCs and 1200m total C2C-Link cable length</li></ul></li><li>• Trigger propagation delay from master to slave devices<ul style="list-style-type: none"><li>– Less than 10 ns for cameras on the same Coaxlink card or on different Coaxlink cards in the same PC</li><li>– Less than 265 ns for cameras on different Coaxlink cards in different PCs (3 PCs and 40m total C2C-Link cable length)</li></ul></li></ul>

## Software

Host PC Operating System	<ul style="list-style-type: none"><li>• Microsoft Windows 10, 8.1, 8, 7 for x86 (32-bit) and x86-64 (64-bit) processor architectures</li><li>• Linux kernel versions 3.10 to 4.10, compatible with a wide range of distributions, tested with CentOS 7, Ubuntu 14.04 and Ubuntu 17.04, for x86 (32-bit) and x86-64 (64-bit) processor architectures</li><li>• Linux kernel version 3.10.96-tegra, tested with Ubuntu 16.04 LTS, for aarch64 (64-bit) processor architecture</li></ul>
APIs	<p>EGrabber class, with C++ and .NET APIs:</p> <ul style="list-style-type: none"><li>• .NET assembly designed to be used with development environments compatible with .NET frameworks version 2.0 or higher</li></ul> <p>GenICam GenTL producer libraries compatible with C/C++ compilers:</p> <ul style="list-style-type: none"><li>• x86 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of x86 applications</li><li>• x86_64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of x86_64 applications</li><li>• aarch64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of aarch64 applications</li></ul>
Memento	Compatible with Memento Event Logging tool

## Environmental conditions

Operating ambient air temperature	0 to +50 °C / +32 to +122 °F
Operating ambient air humidity	10 to 90% RH non-condensing
Storage ambient air temperature	-20 to +70 °C / -4 to +158 °F
Storage ambient air humidity	10 to 90% RH non-condensing



## Certifications

Electromagnetic - EMC standards	<ul style="list-style-type: none"><li>• European Council EMC Directive 2004/108/EC</li><li>• United States FCC rule 47 CFR 15</li></ul>
EMC - Emission	<ul style="list-style-type: none"><li>• EN 55022:2010 Class B</li><li>• FCC 47 Part 15 Class B</li></ul>
EMC - Immunity	<ul style="list-style-type: none"><li>• EN 55024:2010 Class B</li><li>• EN 61000-4-3</li><li>• EN 61000-4-4</li><li>• EN 61000-4-5</li><li>• EN 61000-4-6</li></ul>
Flammability	PCB compliant with UL 94 V-0
RoHS	European Union Directive 2011/65/EU (ROHS2)
REACH	European Union Regulation 1907/2006
WEEE	Must be disposed of separately from normal household waste and must be recycled according to local regulations

## Ordering Information

Product code - Description	<ul style="list-style-type: none"><li>• 1631 - Coaxlink Duo</li></ul>
Optional accessories	<ul style="list-style-type: none"><li>• 1625 - I/O Cable for Grablink DualBase and Coaxlink</li><li>• 1636 - InterPC C2C-Link Adapter</li><li>• 3303 - C2C-Link Ribbon Cable</li><li>• 3304 - HD26F I/O Adapter Cable</li></ul>



## AMERICA

### **Euresys Inc.**

27126-B Paseo Espada - Suite 704  
San Juan Capistrano, CA 92675 - United States  
Phone: +1 949 743 0612  
Email: sales.americas@euresys.com

## EMEA

### **Euresys SA**

Liège Science Park - Avenue du Pré-Aily, 14  
4031 Angleur - Belgium  
Phone: +32 4 367 72 88  
Email: sales.europe@euresys.com

## ASIA

### **Euresys Pte. Ltd.**

750A Chai Chee Road - #07-15 Viva Business Park  
Singapore 469001 - Singapore  
Phone: +65 6445 4800  
Email: sales.asia@euresys.com

## CHINA

### **Euresys Shanghai Liaison Office**

17F, Unit AB, N. 588 Yan An Dong Road - Huangpu District  
CN-200001 Shanghai - China  
Euresys上海联络处  
上海黄浦区 延安东路588号17楼AB座  
200001  
Phone: +86 13817814488  
Email: sales.china@euresys.com

## JAPAN

### **Euresys Japan K.K.**

Expert Office Shinyokohama - Dai 2 Ueno Building, Shinyokohama 3-7-18  
Kouhoku-Ku, Yokohama-Shi 222-0033 - Japan  
〒222-0033  
神奈川県横浜市港北区新横浜3-7-18 第2上野ビル エキスパートオフィス新横浜  
Phone: +81 45 594 7259  
Email: sales.japan@euresys.com

More at [www.euresys.com](http://www.euresys.com)

