


Coaxlink Quad CXP-12 JPEG

Four-connection CoaXPress CXP-12 frame grabber with JPEG compression



둘러보기

- Four 250 MPixels/s JPEG encoders
- Compatible with 8-bit/pixel Bayer CFA cameras
- Two streams per camera: JPEG stream and RGB preview stream
- 4CH CoaXPress CXP-12 연결: 카메라 대역폭 5,000 MB/s
- PCIe 3.0(Gen 3) x8 버스: 버스 대역폭 6,700 MB/s

장점

애플리케이션

The Coaxlink Quad CXP-12 JPEG enables the compact implementation of a multi-channel ultra-high-resolution image acquisition and recording system. The embedded pixel processing drastically reduces the CPU workload to monitor and compress image streams.

Description

- The 4-camera firmware variant of the Coaxlink Quad CXP-12 JPEG implements four independent image acquisition channels with, for each of them, a Bayer CFA decoder and a baseline JPEG encoder that can process up to 250 Megapixels/s, for a total of 1 billion color pixels per second.
- Each channel delivers two concurrent streams: a "JPEG" encoded stream for recording and a "Preview" stream for monitoring.
- The JPEG stream delivers, with a typical latency of only 20 lines, 4:2:2 full-resolution JFIF-compliant encoded images compatible with standard JPEG decoders. The JPEG encoding quality is configurable from 1 to 100.
- The Preview stream provides 8-bit Bayer full-resolution, 24-bit RGB full-resolution or 24-bit RGB low-resolution images.

Support of JFIF image format

The GenICam Browser and GenTL Viewer applications now support JFIF images.

PCIe 3.0(Gen 3) x8 버스

- 피크 버스 대역폭 7,800 MB/s
- 연속 버스 대역폭 6,700 MB/s

가장 빠르고 가장 높은 고해상도 카메라에서 이미지 캡처

- 업계 최고 수준의 데이터 캡처 속도
- 카메라 대 호스트 PC 메모리 대역폭 50 Gbit/s(5,000 MB/s)

Long cable support for Coaxlink CXP-12

- 40 meters at CXP-12 speed (12.5 Gbps)
- CXP-6 속도(6.25 Gbps)에서 72m
- CXP-3 속도(3 Gbps)에서 100m

표준 동축 케이블 사용

- 데이터 전송, 카메라 제어, 트리거, 전원 공급을 하나로 해결할 수 있는 저렴한 케이블
- 가장 혹독한 환경에서도 최고의 신뢰성, 유연성, 성능 제공

고강도 커넥터

- Micro-BNC (HD-BNC) connectors for reliable connection
- 신뢰성 높은 푸시 및 턴, 충격 방식 포지티브 락
- 빠르고 쉬운 연결 및 연결 해제 가능

하나의 Coaxlink 카드에 최대 4대의 카메라 연결 가능

Memento Event Logging Tool

- Memento is an advanced development and debugging tool available for Coaxlink cards.
- Memento records an accurate log of all the events related to the camera, the frame grabber and its driver as well as the application.
- It provides the developer with a precise timeline of time-stamped events, along with context information and logic analyzer view.
- 애플리케이션 개발, 디버깅뿐 아니라 기계 운용 중에도 유용한 장점을 제공합니다.

GPU 직접 전송

- AMD DirectGMA 및 NVIDIA(CUDA) 샘플 프로그램 제공 가능
- Direct GPU transfer eliminates unnecessary system memory copies, lowers CPU overhead, and reduces latency, resulting in significant performance improvements in data transfer times for applications.
- AMD DirectGMA를 사용하여 이미지 데이터를 GPU 메모리로 직접 캡처. AMD FirePro W5x00 이상 제품 및 모든 AMD FirePro S 시리즈 제품과 호환

범용 IO 라인

- 광범위한 센서 및 모션 인코더와 호환:
- 고속 차동 입력: 최대 5 MHz까지 지원하는 쿼드러처 모션 인코더.
- 절연 전류 감지 입력: 5V, 12V, 24V 신호 전압 인가 가능, 최대 50 kHz, 최대 500VAC RMS의 갈바닉 개별 절연.
- 절연 접점 출력.
- 고속 5V 규격 TTL 입력/LVTTL 출력.

고성능 DMA(Direct Memory Access)

- Direct transfer into user-allocated memory and hardware boards that expose PCI addresses
- 하드웨어 분산-수집(scatter-gather) 지원
- 64비트 주소 지정 기능

Coaxlink 드라이버에는 다음과 같은 도구가 포함되어 있습니다:

- Genicam Browser: An application giving access to the Genicam features exposed by the GenTL Producer(s) in the system.
- GenTL 콘솔: Euresys GenTL Producer에 의해 노출된 함수와 명령에 대한 액세스를 제공하는 커맨드 라인 툴.

Area 스캔 트리거 기능

- 트리거는 일부분이 위치에 들어 왔을 때 캡처를 시작하는 데 사용됩니다. 하드웨어 트리거는 Coaxlink의 I/O 라인에서 제공됩니다. 소프트웨어 트리거는 애플리케이션에서 제공됩니다.
- 옵션 트리거 지연을 사용하여 프로그래밍 가능한 시간 동안 캡처를 연기할 수 있습니다.
- 트리거 제거 기능은 일부 트리거를 무시하는 기능입니다.

- 카메라 노출 제어 기능을 사용하면 애플리케이션에서 카메라의 노출 시간을 제어할 수 있습니다.
- 캡처가 시작되면 적절한 시점에 Coaxlink 보드가 출력 라인 중 하나에 연결된 조명 장치를 제어하기 위한 신호를 생성합니다.

Compliant with Genicam Including support for

- GenApi
- 표준 기능 명명 규칙(SFNC)
- GenTL

Windows, Linux 및 macOS 드라이버 이용 가능

- Including support for Intel 32-bit and 64-bit platforms as well as ARM 64-bit platforms

애플리케이션

비디오 캡처 및 기록

- 동작 분석 및 기록용 고 프레임 레이트 비디오 캡처

비디오 모니터링, 감시, 보안

- 장거리 동축 케이블을 통해 교통 감시, 모니터링, 통제용 HD 비디오 전송 및 캡처

사양

Mechanical

Form Factor	PCI Express card
Format	Standard profile, half length, 8-lane PCI Express card
Cooling method	Air cooling, fan-cooled heatsink
Mounting	For insertion in a standard height, 8-lane or higher, PCI Express card slot
Connectors	• 'A', 'B', 'C', 'D' on bracket: – 4x Micro-BNC female connectors – CoaXpress host interface • EXTERNAL I/O' on bracket: – 26-pin 3-row high-density female sub-D connector – I/O lines and power output • INTERNAL I/O 1' and 'INTERNAL I/O 2' on PCB: – 2x 26-pin 2-row 0.1" pitch pin header with shrouding – I/O lines and power output • 'AUXILIARY POWER INPUT' on module: – 6-pin PEG power socket – 12 VDC power input for PoCXP camera(s) and I/O power • 'C2C-LINK' on module: – 6-pin 2-row 0.1-in header – Card to card link

Lamp indicators	• 'A', 'B', 'C', 'D' on bracket: – 4x bi-color red/green LEDs – CoaXPress Host connector indicator lamps • 'FPGA STATUS LAMP' on PCB: – Bi-color red/green LED – FPGA status lamp • 'BOARD STATUS LAMP' on PCB: – Bi-color red/green LED
Switches	'RECOVERY' on card PCB: • 3-pin 1-row 0.1" header • Firmware emergency recovery
Dimensions	L 167.65 mm x H 111.15 mm L 6.6 in x H 4.38 in
Weight	196 g, 6.91 oz

Host bus

Standard	PCI Express 3.0
Link width	• 8 lanes • 1 lane, 2 lanes or 4 lanes with reduced performance
Link speed	• 8.0 GT/s (PCIe 3.0) • 5.0 GT/s (PCIe 2.0) with reduced performance
Maximum payload size	512 bytes
DMA	32- and 64-bit
Peak delivery bandwidth	7,800 MB/s
Effective (sustained) delivery bandwidth	6,700 MB/s (Host PC motherboard dependent)
Power consumption	Typ. TBW (TBD W @ +3.3V, TBD W @ +12V), excluding camera and I/O power output

Camera / video inputs

Interface standard(s)	CoaXPress 1.0, 1.1, 1.1.1 and 2.0
Connectors	4x Micro-BNC 75 Ohms (also known as HD-BNC™) CXP-12
Status LEDs	1 CoaXPress Host connection status per connector
Number of cameras	Four 1-connection area-scan cameras
Line-scan cameras supported	No
Maximum aggregated camera data transfer rate	50 Gbit/s (5,000 MB/s)
Supported CXP down-connection speeds	1.25 GT/s (CXP-1), 2.5 GT/s (CXP-2), 3.125 GT/s (CXP-3), 5 GT/s (CXP-5), 6.25 GT/s (CXP-6), 10.0 GT/s (CXP-10), and 12.5 GT/s (CXP-12)
Number of CXP data streams (per camera)	1 data stream per camera
Maximum CXP stream packet size	16,384 bytes
PoCXP (Power over CoaXPress)	• PoCXP Safe Power: – 17 W of 24V DC regulated power per CoaXPress connector – PoCXP Device detection and automatic power-on – Overload and short-circuit protections • On-board 12V to 24V DC/DC converter • A +12V power source must be connected to the AUXILIARY POWER INPUT connector using a 6-pin PEG cable

Camera types	Area-scan cameras: • 8-bit Bayer CFA single-tap (1X-1Y) progressive-scan • Image resolution (H x V): from 128 x 16 up to 5120 x 3840; width and height must be multiples of 8
Camera pixel formats supported	Bayer (PFNC names): • BayerGR8, BayerRG8, BayerGB8, BayerBG8

Area-scan camera control

Trigger	• Precise control of asynchronous reset cameras, with exposure control. • Support of camera exposure/readout overlap. • Support of external hardware trigger, with optional delay and trigger decimation.
Strobe	• Accurate control of the strobe position for strobed light sources. • Support of early and late strobe pulses.

On-board processing

On-board memory	2 GB
Image data stream processing	• Optional swap of R and B components • 1:8 image downscaling available on RGB8 output (Stream0, a.k.a. "preview stream")
Bayer CFA to RGB decoder	Advanced interpolation method available for: • 4-camera firmware variant
Data stream statistics	• Measurement of: – Frame rate (Area-scan only) – Line rate – Data rate • Configurable averaging interval
Event signaling and counting	• The application software can be notified of the occurrence of various events: – Standard event: the EVENT_NEW_BUFFER event notifies the application of newly filled buffers – A large set of custom events • Custom events sources: – I/O Toolbox events – Camera and Illumination control events – CoaXPress data stream events – CoaXPress host interface events • Each custom event is associated with a 32-bit counter that counts the number of occurrences • The last three 32-bit context data words of the event context data can be configured with event-specific context data: – Event-specific data – State of all System I/O lines sampled at the event occurrence time – Value of any event counter

On-board video codec

Video encoders	JPEG • Baseline profile • 4 encoders • Up to 250 Mpixels/second per encoder • JFIF compliant output
----------------	--

General Purpose Inputs and Outputs

Number of lines	20 I/O lines: • 4 differential inputs (DIN) • 4 singled-ended TTL inputs/outputs (TTLIO) • 8 isolated inputs (IIN) • 4 isolated outputs (IOUT) NOTE: The number of I/O lines can be extended using I/O modules attached to the I/O EXTENSION connector.
Usage	• Any I/O input lines can be used by any LIN tool of the I/O Toolbox • Selected pairs of I/O input lines can be used by any QDC tool of the I/O toolbox to decode A/B signals of a motion encoder • The LIN and QDC tools outputs can be further processed by the other tools (DIV, MDV, DEL) of the I/O toolbox to generate any of the following "trigger" events: – The "cycle trigger" of the Camera and Illumination controller – The "cycle sequence trigger" of the Camera and Illumination controller
Electrical specifications	• DIN: High-speed differential inputs compatible with ANSI/EIA/TIA-422/485 differential line drivers and complementary TTL drivers • TTLIO: High-speed 5V-compliant TTL inputs or LVTTTL outputs, compatible with totem-pole LVTTTL, TTL, 5V CMOS drivers or LVTTTL, TTL, 3V CMOS receivers • IIN: Isolated current-sense inputs with wide voltage input range up to 30V, compatible with totem-pole LVTTTL, TTL, 5V CMOS drivers, RS-422 differential line drivers, potential free contacts, solid-state relays and opto-couplers • IOUT: Isolated contact outputs compatible with 30V / 100mA loads
Filter control	• Glitch removal filter available on all System I/O input lines • Configurable filter time constants: – for DIN and TTLIO lines: 50 ns, 100 ns, 200 ns, 500 ns, 1 μs – for IIN lines: 500 ns, 1 μs, 2 μs, 5 μs, 10 μs
Polarity control	Yes
Power output	Non-isolated, +12V, 1A, with electronic fuse protection
I/O Toolbox tools	The I/O Toolbox is a configurable interconnection of tools that generates events (usually triggers) from input lines. The composition of the toolset is product- and firmware-dependent. • Line Input tool (LIN): Edge detector delivering events on rising or falling edges of any selected input line. • Quadrature Decoder tool (QDC): A composite tool including: – A quadrature edge detector delivering events on selected transitions of selected pairs of input lines. – An optional backward motion compensator for clean line-scan image acquisition when the motion is unstable. – A 32-bit up/down counter for delivering a position value. • Divider tool (DIV): to generate an event every nth input events from any I/O toolbox event source. • Multiplier/divider tool (MDV): to generate m events every d input events from any I/O toolbox event source. • Delay tool (DEL): to delay up to 16 events from one or two I/O toolbox event sources, by a programmable time or number of motion encoder ticks (any QDC events). • User Actions Scheduler tool (UAS): to delegate the execution of User Actions at a scheduled time or encoder position. Possible user actions include setting low/high/toggle any bit of the User Output Register or generation of any User Events.
I/O Toolbox composition	Firmware-dependent I/O toolbox composition: • 4-camera: 8 LIN, 4 QDC, 4 DIV, 4 MDV, 4 DEL, 1 UAS

C2C-Link

Description	• Allows to accurately synchronize the trigger and start-of-exposure of multiple grabber-controlled area-scan cameras. • C2C-Link is able to synchronize cameras connected – to the same Coaxlink card – to different cards in the same PC (requires an accessory cable such as the "3303 C2C-Link Ribbon Cable" or a custom-made C2C-Link cable) – to different cards in different PCs (requires one "1636 InterPC C2C-Link Adapter" for each PC and one RJ 45 CAT 5 STP straight LAN cable for each adapter but the last one)
Specification	• Maximum distance – 60 cm inside a PC – 1200 m cumulated adapter to adapter cable length • Maximum trigger rate – 2.5 MHz for configurations using a single PC, or up to 10 PCs and 100 m total C2C-Link cable length – 200 kHz for configurations up to 32 PCs and 1200m total C2C-Link cable length • Trigger propagation delay from master to slave devices – Less than 10 ns for cameras on the same Coaxlink card or on different Coaxlink cards in the same PC – Less than 265 ns for cameras on different Coaxlink cards in different PCs (3 PCs and 40m total C2C-Link cable length)

Software

Host PC Operating System	• Microsoft Windows 10, 8.1, 7 for x86 (32-bit) and x86-64 (64-bit) processor architectures • Linux for x86 (32-bit), x86-64 (64-bit) and aarch64 (64-bit) processor architectures • macOS for x86-64 (64-bit) processor architecture Refer to release notes for details
APIs	EGrabber class, with C++ and .NET APIs: • .NET assembly designed to be used with development environments compatible with .NET frameworks version 2.0 or higher GenICam GenTL producer libraries compatible with C/C++ compilers: • x86 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of x86 applications • x86_64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of x86_64 applications • aarch64 dynamic library designed to be used with ISO-compliant C/C++ compilers for the development of aarch64 applications
Memento	Compatible with Memento Event Logging tool

Environmental conditions

Operating ambient air temperature	0 to +55 °C / +32 to +131 °F
Operating ambient air humidity	10 to 90% RH non-condensing
Storage ambient air temperature	-20 to +70 °C / -4 to +158 °F
Storage ambient air humidity	10 to 90% RH non-condensing

Certifications

Electromagnetic - EMC standards	• European Council EMC Directive 2004/108/EC • United States FCC rule 47 CFR 15
EMC - Emission	• EN 55022:2010 Class B • FCC 47 Part 15 Class B

EMC - Immunity	• EN 55024:2010 Class B • EN 61000-4-3 • EN 61000-4-4 • EN 61000-4-6
Flammability	PCB compliant with UL 94 V-0
RoHS	European Union Directive 2011/65/EU (ROHS2)
REACH	European Union Regulation 1907/2006
WEEE	Must be disposed of separately from normal household waste and must be recycled according to local regulations

Ordering Information

Product code - Description	• 3620 - Coaxlink Quad CXP-12 JPEG
Optional accessories	• 1625 - DB25F I/O Adapter Cable • 1636 - InterPC C2C-Link Adapter • 3303 - C2C-Link Ribbon Cable • 3304 - HD26F I/O Adapter Cable • 3610 - HD26F I/O Extension Module TTL-RS422 • 3612 - HD26F I/O Extension Module TTL-CMOS5V-RS422 • 3613 - JTAG Adapter Xilinx for Coaxlink



EMEA

Euresys SA

Liège Science Park - Avenue du Pré Aily, 14
4031 Angleur - Belgium

Phone: +32 4 367 72 88

Email: sales.europe@euresys.com

EMEA

Sensor to Image GmbH

Lechtorstrasse 20 -
86956 Schongau - Germany

Phone: +49 8861 2369 0

Email: sales.europe@euresys.com

AMERICA

Euresys Inc.

27126-B Paseo Espada - Suite 704
San Juan Capistrano, CA 92675 - United States

Phone: +1 949 743 0612

Email: sales.americas@euresys.com

ASIA

Euresys Pte. Ltd.

750A Chai Chee Road - #07-15 Viva Business Park
Singapore 469001 - Singapore

Phone: +65 6445 4800

Email: sales.asia@euresys.com

CHINA

Euresys Shanghai Liaison Office

Unit 802, Tower B, Greenland The Center - No.500 Yunjin Road, Xuhui District
200232 Shanghai - China

Euresys上海联络处

上海市徐汇区云锦路500号绿地汇中心B座802室
200232

Phone: +86 21 33686220

Email: sales.china@euresys.com

JAPAN

Euresys Japan K.K.

Expert Office Shinyokohama - Nisso Dai 18 Building, Shinyokohama 3-7-18
Kouhoku-Ku, Yokohama-Shi 222-0033 - Japan

〒222-0033

神奈川県横浜市港北区新横浜3-7-18 日総第18ビル エキスパートオフィス新横浜

Phone: +81 45 594 7259

Email: sales.japan@euresys.com

More at www.euresys.com

